

CAPACITORES PARA ARRANQUE DE MOTORES (VALORES RECOMENDADOS)

POTENCIA EN HP	CAPACIDAD APROXIMADA
1/8 HP	60 / 70 MF - 70 / 80 MF
1/6 HP	80 / 100 MF - 100 / 120 MF
1/4 HP	120 / 140 MF - 140 / 170 MF
1/3 HP	170 / 200 MF - 200 / 230 MF
1/2 HP	230 / 260 MF
3/4 HP	260 - 300 MF
1 HP	300 / 350 MF
1.5 HP	350 / 400 MF - 380 / 420 MF
2 HP	400 / 460 MF
2.5 HP	460 / 530 MF

EQUIVALENCIAS EN CAPACITORES DE ARRANQUE

110 Vca.	220 Vca.	330 Vca.
60 / 70 MF	60 / 70 MF	50 / 60 MF
70 / 90 MF	70 / 90 MF	70 / 90 MF
80 / 100 MF	80 / 100 MF	80 / 100 MF
100 / 120 MF	100 / 120 MF	100 / 120 MF
120 / 140 MF	120 / 140 MF	101 / 107 MF
140 / 160 MF	140 / 160 MF	120 / 140 MF
170 / 190 MF	170 / 190 MF	140 / 160 MF
190 / 210 MF	190 / 210 MF	170 / 190 MF
240 / 270 MF	210 / 240 MF	210 / 240 MF
270 / 310 MF	270 / 310 MF	-
320 / 360 MF	320 / 360 MF	-
350 / 400 MF	350 / 400 MF	-
380 / 420 MF	380 / 420 MF	-
400 / 430 MF	400 / 430 MF	-
450 / 500 MF	450 / 500 MF	-
500 / 600 MF	500 / 600 MF	-
600 / 700 MF	-	-
700 / 800 MF	-	-